

# Fieldbus device Operation Manual



## EX260 Series for EtherNet/IP™

Thank you for purchasing an SMC EX260 Series Fieldbus device (Hereinafter referred to as "SI unit"). Please read this manual carefully before operating the product and make sure you understand its capabilities and limitations. Please keep this manual handy for future reference.

To obtain more detailed information about operating this product, please refer to the SMC website (URL <http://www.smcworld.com>) or contact SMC directly.

## Safety Instructions

These safety instructions are intended to prevent hazardous situations and/or equipment damage. These instructions indicate the level of potential hazard with the labels of "Caution", "Warning" or "Danger". They are all important notes for safety and must be followed in addition to International standards (ISO/IEC) and other safety regulations.

**Caution:** CAUTION indicates a hazard with a low level of risk which, if not avoided, could result in minor or moderate injury.

**Warning:** WARNING indicates a hazard with a medium level of risk which, if not avoided, could result in death or serious injury.

**Danger:** DANGER indicates a hazard with a high level of risk which, if not avoided, will result in death or serious injury.

### Operator

- This operation manual is intended for those who have knowledge of machinery using pneumatic equipment, and have sufficient knowledge of assembly, operation and maintenance of such equipment. Only those persons are allowed to perform assembly, operation and maintenance.
- Read and understand this operation manual carefully before assembling, operating or providing maintenance to the product.

## Safety Instructions

### Warning

Do not disassemble, modify (including changing the printed circuit board) or repair. An injury or failure can result.

Do not operate the product outside of the specifications. Do not use for flammable or harmful fluids. Fire, malfunction, or damage to the product can result. Verify the specifications before use.

Do not operate in an atmosphere containing flammable or explosive gases. Fire or an explosion can result. This product is not designed to be explosion proof.

If using the product in an interlocking circuit: Provide a double interlocking system, for example a mechanical system. Check the product regularly for proper operation. Otherwise malfunction can result, causing an accident.

The following instructions must be followed during maintenance: Turn off the power supply. Stop the air supply, exhaust the residual pressure and verify that the air is released before performing maintenance. Otherwise an injury can result.

### Caution

After maintenance is complete, perform appropriate functional inspections. Stop operation if the equipment does not function properly. Safety cannot be assured in the case of unexpected malfunction.


Provide grounding to assure the safety and noise resistance of the Serial system. Individual grounding should be provided close to the product with a short cable.

### NOTE

- The direct current power supply to combine should be UL1310 Class2 power supply when conformity to UL is necessary.

## Summary of Product elements

<EX260-SEN1/-SEN2/-SEN3/-SEN4>



No.	Element	Description
1	Fieldbus interface connector (BUS OUT)	EtherNet/IP™ connection PORT 2 (M12 4-pin socket, D-coded)
2	Fieldbus interface connector (BUS IN)	EtherNet/IP™ connection PORT 1 (M12 4-pin socket, D-coded)
3	Power supply connector	Power supply with load voltage for valves and operating voltage for SI unit (M12 4-pin plug, A-coded)
4	Ground terminal	Functional earth (M3 screw)
5	Output connector	Output signal interface for valve manifold
6	LED	Bus status-specific and SI unit-specific LEDs
7	Mounting hole	Mounting hole for connection to the valve manifold


### Accessories

Hexagon socket head cap screw	2 pcs. M3 x 30 screw for connection to the valve manifold
Seal cap	1 pc. seal cap for unused fieldbus interface connector (BUS OUT)

## Connecting cables


Select the appropriate cables to mate with the connectors mounted on the SI unit.

### Fieldbus interface connector layout



BUS OUT: M12 4-pin socket D-coded


No.	Designation	Description
1	TD+	Transmit Data +
2	RD+	Receive Data +
3	TD-	Transmit Data -
4	RD-	Receive Data -



BUS IN: M12 4-pin socket D-coded

No.	Designation	Description
1	TD+	Transmit Data +
2	RD+	Receive Data +
3	TD-	Transmit Data -
4	RD-	Receive Data -

### Power supply connector layout



PWR: M12 4-pin plug A-coded

No.	Designation	Description
1	SI24 V	+24 V for SI unit operation
2	SV24 V	+24 V for solenoid valve
3	SI0 V	0 V for SI unit operation
4	SV0 V	0 V for solenoid valve


### Ground terminal

Connect the ground terminal to ground. Resistance to ground should be 100 ohms or less.

## Setting

### Output number assignment

Output numbering starts at zero and refers to the solenoid position on the manifold.



## LED indication




LED	LED Status	Description
NS	<input type="checkbox"/> OFF	The SI unit operating voltage is not supplied or the IP address is not set.
	<input checked="" type="checkbox"/> Green ON	EtherNet/IP™ communications established.
	<input checked="" type="checkbox"/> Green flashing	EtherNet/IP™ communications not established.
	<input checked="" type="checkbox"/> Red flashing	EtherNet/IP™ communications time out.
MS	<input checked="" type="checkbox"/> Red ON	IP address duplicated.
	<input type="checkbox"/> OFF	The SI unit operating voltage is not supplied.
	<input checked="" type="checkbox"/> Green ON	Operating normally.
LA/1	<input checked="" type="checkbox"/> Green flashing	Setting error.
	<input checked="" type="checkbox"/> Red flashing	Recoverable error.
	<input checked="" type="checkbox"/> Red ON	Unrecoverable error.
LA/2	<input type="checkbox"/> OFF	BUS IN side: No Link, No Activity
	<input checked="" type="checkbox"/> Green ON	BUS IN side: Link, No Activity
LA/2	<input checked="" type="checkbox"/> Green flashing	BUS IN side: Link, Activity
	<input type="checkbox"/> OFF	BUS OUT side: No Link, No Activity
LA/2	<input checked="" type="checkbox"/> Green ON	BUS OUT side: Link, No Activity
	<input checked="" type="checkbox"/> Green flashing	BUS OUT side: Link, Activity
PWR(V)	<input checked="" type="checkbox"/> Green ON	Load voltage for the valve is supplied
	<input type="checkbox"/> OFF	Load voltage for the valve is not supplied or is outside the tolerance range (19 V or less)

## Installation

### General instructions on installation and maintenance

Connect valve manifold to the SI unit. Connectable valve manifolds are the same as for EX250 series SI unit. Refer to the EX250 series valve manifold section in the valve catalogue for valve manifold dimensions.

### Assembly and disassembly of the SI unit



### Replacement of the SI unit

- Remove the M3 hexagon screws from the SI unit and release the SI unit from the valve manifold.
- Replace the SI unit.
- Tighten the screws with the specified tightening torque. (0.6 Nm)

### Precautions for maintenance


- Be sure to switch off the power.
- Check there is no foreign matter inside the SI unit.
- Check there is no damage and no foreign matter on the gasket.
- Be sure to tighten the screws with the specified torque.

If the SI unit is not assembled properly, inside PCBs may be damaged or liquid and/or dust may enter into the unit.

## Setting

### Switch setting

The switches should only be set with the power supply turned off. Open the cover and set the rotary switches and DIP switch with a small flat blade screwdriver.



### Configuration

In order to configure the SI unit for the EtherNet/IP™ network, the appropriate device master file (EDS file) for the SI unit will be required.

Technical documentation giving detailed configuration information and the EDS file can be found on the SMC website (URL <http://www.smcworld.com>).

### EDS file

	Model number	EDS file
1	EX260-SEN1	ex260_sen1_24_v++.eds
2	EX260-SEN2	ex260_sen2_24_v++.eds
3	EX260-SEN3	ex260_sen3_22_v++.eds
4	EX260-SEN4	ex260_sen4_22_v++.eds

## Troubleshooting

Technical documentation giving detailed troubleshooting information can be found on the SMC website (URL <http://www.smcworld.com>).

## Specifications

Connected load: 24 VDC Solenoid valve with surge voltage suppressor of 1.5 W or less (manufactured by SMC)

Current consumption of power supply for SI unit operation: 0.1 A max.  
Ambient temperature for operation: -10 to 50 °C  
Ambient temperature for storage: -20 to 60 °C  
Pollution degree 3: (UL508)

Technical documentation giving detailed specification information can be found on the SMC website (URL <http://www.smcworld.com>).

## Outline Dimensions

Technical documentation giving detailed outline dimensions information can be found on the SMC website (URL <http://www.smcworld.com>).

## Accessories

Technical documentation giving detailed accessories information can be found on the SMC website (URL <http://www.smcworld.com>).

SMC Corporation URL <http://www.smcworld.com>

Akihara UDX 15F, 4-14-1, Sotokanda, Chiyoda-ku, Tokyo 101-0021, JAPAN  
Phone: +81 3-5207-8249 Fax: +81 3-5298-5362

Note: Specifications are subject to change without prior notice and any obligation on the part of the manufacturer. EtherNet/IP™ is a trademark of ODVA. © 2012 SMC Corporation All Rights Reserved